

Setting up the Philips Xenium X710 for WAP over GPRS

Setting up the WAP account

1. On the handset, press the **Menu** button.
2. Scroll to **Browser** and press **Select**.
3. Scroll to **Data account** and press **Select**.
4. Scroll to **GPRS** and press **Select**.
5. Scroll to an **empty profile** and press **Edit**.
6. Select **Account name** and press **Edit**.
7. Enter **[optus wap]** and press **Done**.
8. Scroll to **APN** and press **Edit**.
9. Enter **[wap.optus.net.au]** and press **Done**.
10. Scroll to **Username** and press **Edit**.
11. Enter **[Leave blank]** and press **Done**.
12. Scroll to **Password** and press **Edit**.
13. Enter **[Leave blank]** and press **Done**.
14. Scroll to **Auth. Type** and change to **Normal**.
15. Press **Done**.
16. Press **Yes** to save the profile.
17. Press **Back** twice.
18. Scroll to **WAP** and press **Select**.
19. Scroll to **Settings** and press **Select**.
20. Scroll to **Edit profile** and press **Select**.
21. Scroll to an empty profile and press **Select**.
22. Scroll to **Edit profile** and press **Select**.
23. Scroll to **Rename profile** and press **Edit**.
24. Enter **[optus wap]** and press **Done**.
25. Scroll to **Home** and press **Select**.
26. Enter **[http://networker.optus.net.au/wap/index.wml]** and press **Done**.
27. Scroll to **Data account** and press **Select**.
28. Scroll to **GPRS** and press **Select**.
29. Scroll to **[optus wap]** and press **Select**.
30. Scroll to **Connection type** and press **Select**.
31. Highlight **WAP** and press **Select**.
32. Enter **[202.139.083.152]**.
33. Scroll to **Security** and select **Off**.
34. Press **Done**.
35. Scroll to **Username** and press **Edit**.
36. Enter **[Leave blank]** and press **Done**.
37. Scroll to **Password** and press **Edit**.
38. Enter **[Leave blank]** and press **Done**.
39. Press **Yes** to save.
40. Scroll to **Activate profile** and press **Select**.
41. Press the hangup key to return to the main menu.
10. Scroll to **Username** and press **Edit**.
11. Enter **[Leave blank]** and press **Done**.
12. Scroll to **Password** and press **Edit**.
13. Enter **[Leave blank]** and press **Done**.
14. Scroll to **Auth. Type** and change to **Normal**.
15. Press **Done**.
16. Press **Yes** to save the profile.
17. Press **Back** twice.
18. Scroll to **WAP** and press **Select**.
19. Scroll to **Settings** and press **Select**.
20. Scroll to **Edit profile** and press **Select**.
21. Scroll to an empty profile and press **Select**.
22. Scroll to **Edit profile** and press **Select**.
23. Scroll to **Rename profile** and press **Edit**.
24. Enter **[optus internet]** and press **Done**.
25. Scroll to **Data account** and press **Select**.
26. Scroll to **GPRS** and press **Select**.
27. Scroll to **[optus internet]** and press **Select**.
28. Scroll to **Connection type** and press **Select**.
29. **HTTP** is set by default.
30. Scroll to **Username** and press **Edit**.
31. Enter **[Leave blank]** and press **Done**.
32. Scroll to **Password** and press **Edit**.
33. Enter **[Leave blank]** and press **Done**.
34. Press **Done**.
35. Press **Yes** to save.
36. Press the hangup key to return to the main menu.

Setting up the Internet account

1. On the handset, press the **Menu** button.
2. Scroll to **Browser** and press **Select**.
3. Scroll to **Data account** and press **Select**.
4. Scroll to **GPRS** and press **Select**.
5. Scroll to an **empty profile** and press **Edit**.
6. Select **Account name** and press **Edit**.
7. Enter **[optus internet]** and press **Done**.
8. Scroll to **APN** and press **Edit**.
9. Enter **[internet]** and press **Done**.
10. Scroll to **Username** and press **Edit**.
11. Enter **[Leave blank]** and press **Done**.
12. Scroll to **Password** and press **Edit**.
13. Enter **[Leave blank]** and press **Done**.
14. Scroll to **Auth. Type** and change to **Normal**.
15. Press **Done**.
16. Press **Yes** to save the profile.
17. Press **Back** twice.
18. Scroll to **WAP** and press **Select**.
19. Scroll to **Settings** and press **Select**.
20. Scroll to **Edit profile** and press **Select**.
21. Scroll to an empty profile and press **Select**.
22. Scroll to **Edit profile** and press **Select**.
23. Scroll to **Rename profile** and press **Edit**.
24. Enter **[optus wap]** and press **Done**.
25. Scroll to **Home** and press **Select**.
26. Enter **[http://networker.optus.net.au/wap/index.wml]** and press **Done**.
27. Scroll to **Data account** and press **Select**.
28. Scroll to **GPRS** and press **Select**.
29. Scroll to **[optus wap]** and press **Select**.
30. Scroll to **Connection type** and press **Select**.
31. Highlight **WAP** and press **Select**.
32. Enter **[202.139.083.152]**.
33. Scroll to **Security** and select **Off**.
34. Press **Done**.
35. Scroll to **Username** and press **Edit**.
36. Enter **[Leave blank]** and press **Done**.
37. Scroll to **Password** and press **Edit**.
38. Enter **[Leave blank]** and press **Done**.
39. Press **Yes** to save.
40. Scroll to **Activate profile** and press **Select**.
41. Press the hangup key to return to the main menu.

Setting up the Email profile

1. On the handset, press the **Menu** button.
2. Scroll to **Messaging** and press **Select**.
3. Scroll to **E-mail** and press **Select**.
4. Scroll to **E-mail accounts** and press **Select**.
5. Highlight an empty profile and press **Options**.
6. Scroll to **Edit** and press **Select**.
7. Scroll to **E-mail address** and press **Edit**.
8. Enter **[youremail@domain.com]** and press **Done**.
9. Scroll to **Display name** and press **Edit**.
10. Enter **[Your Email]** and press **Done**.
11. Scroll to **Username** and press **Edit**.
12. Enter **[You User Name]** and press **Done**.
13. Scroll to **Password** and press **Edit**.
14. Enter **[*****]** and press **Done**.
15. Scroll to **Outgoing server** and press **Edit**.
16. Enter **[mail.optusnet.com.au]** and press **Done**.
17. Scroll to **Incoming server** and press **Edit**.
18. Enter **[mail.optusnet.com.au]** and press **Done**.
19. Scroll to **Advanced settings** and press **Select**.
20. Scroll to **Account settings** and press **Select**.
21. Scroll to **Account name** and press **Edit**.
22. Enter **[optus]** and press **Done**.
23. Scroll to **Data Account** and press **Select**.
24. Scroll to **GPRS** and press **Select**.
25. Scroll to **[optus internet]** and press **Select**.
26. Press **Done**.
27. Press **Yes** to save changes.
28. Press **Back**.
29. Press **Done**.
30. Press **Yes** to save changes.
31. Scroll to **Activate** and press **Select**.
32. Press the hangup key to return to the main menu.